

Code No: R31046**R10****Set No: 1**

- 7) a) For (7,4) linear block code, determine the generator matrix and decode the code word 1101101.
b) Write short notes on 'BCH codes'.
- 8) a) Discuss the advantages and disadvantages of convolution codes over block codes.
b) Describe exhaustive search method of decoding convolution code.

All JNTU WORLD

Code No: R31046

R10

Set No: 3

III B.Tech. I Semester Regular and Supplementary Examinations, December - 2013

DIGITAL COMMUNICATIONS

(Electronics and Communication Engineering)

Time: 3 Hours

Max Marks: 75

Answer any FIVE Questions
All Questions carry equal marks

- 1) a) An analog wave form with an amplitude range from -10 volts to +10 volts and a band width of 200HZ is to be PCM-ed and transmitted with an accuracy of +0.2% of the dynamic range of the signal Determine the following.
 - (i) The min – sampling rate needed.
 - (ii) The no of bits / code word.
 - (iii) The min bit rate needed.
 - (iv) The min transmission bandwidth needed.
 b) What the need of DPCM? Explain, its principle of working.
- 2) a) Explain the working of ADM system with a discrete set of values for step size.
b) Derive an expression for SNR for DM system.
- 3) a) Show that BPSK is superior to ASK by 3dB in the average signal power requirement with necessary mathematical equations.
b) Bring out the differences between DPSK and DEPSK.
- 4) a) Explain the basic structure of a binary baseband receiver with a neat block diagram.
b) Explain the operation of a non coherent BFSK receiver.
- 5) a) For a lossless channel show that $H(X/Y) = 0$
b) Consider a telegraph source having two symbols dot and dash. The dot duration is 0.2 seconds the dash duration is 3 times the dot duration. The probability of dots occurring is twice that of the dash and the time between the symbols is 0.2 seconds calculate the information rate of the telegraph code.
- 6) a) A DMS had 4 symbols x_1, x_2, x_3 and x_4 with probabilities $1/2, 1/4, 1/8$ and $1/8$ respectively Construct a Shannon fanon code for x. Show that this code had the optimum property that $n_i = I(x_i)$ and the code efficiency is 100%.
b) Show the channel capacity of an ideal AWGN channel with infinite bandwidth is given by $C_\infty = 1.44 \frac{s}{\eta}$ b/s where s is the average signal power and $\frac{\eta}{2}$ is power spectral density of white Gaussian noise.

Code No: R31046

R10

Set No: 3

7) a) Consider a (7,4) code whose generator matrix is

$$G = \begin{bmatrix} 1 & 1 & 1 & : & 1 & 0 & 0 & 0 \\ 1 & 0 & 1 & : & 0 & 1 & 0 & 0 \\ 0 & 1 & 1 & : & 0 & 0 & 1 & 0 \\ 1 & 1 & 0 & : & 0 & 0 & 0 & 1 \end{bmatrix}$$

- i) Obtain all code words
- ii) Find the parity check matrix H
- iii) Compute the syndrome for received vector 11 01 101. If this a valid code?

b) Discusses the error correction capabilities of lineal block codes.

8) a) An convolution encoder is described by the polynomials.

$$g_1(x) = 1+x+x^2$$

$$g_2(x) = x+x^2$$

- For this encoder
- i) Find the connection vectors
 - ii) Draw the state diagram.
 - iii) Find the impulse response
 - iv) Find the output for a message input 1010.

b) Explain sequential decoding of convolutional code.
